

San Diego Stat University

- (3/22)

In order to be able to say **anything** useful we have to make simplifying assumptions, *e.g* simultaneous diagonalizability.

We looked at **time-split schemes** as a practical way to route around some (size / complexity) of the computational challenges. (Stability and Boundary Conditions are a different story...)

for which $b_{11}, b_{22} > 0$ and $b_{12}^2 < b_{11} \cdot b_{22}$ for parabolicity; and constant (for now).

Initially, we will consider the case $b_{12} = 0$ (no mixed derivative), on a square domain...

SAN DIEGO ST UNIVERSIT

Introduction Crank-Nicolson / ADI on a 2D Square The Alternating Direction Implicit Method ADI Algorithms Implementing ADI Methods

Introduction Crank-Nicolson / ADI on a 2D Square

Crank-Nicolson in a Cube

Figure: [LEFT] The matrix which must be inverted in each Crank-Nicolson iteration. If we trade storage of the LU-factorization [CENTER, RIGHT] for speed, then here with $6 \times 6 \times 6$ interior points, we end up needing more than 10 times the storage. For 20^3 (30^3) interior points, the requirement jumps from 53,600 (183,600) matrix entries, to just over 6,000,000 (47,000,000) — a factor of 114 (256). The band-width grows quadratically $\mathcal{O}(n^2)$, and the LU-factorization fills in the whole bandwidth. $LU_{time}^{Matlab} = 8.5s$ (143.6s).



If we use the Crank-Nicolson schemes (for 3 spatial dimensions), we end up having to invert a hepta-diagonal matrix in each iteration.

2)	Peter Blomgren, $\langle \texttt{blomgren.peter@gmail.com} \rangle$	Systems of PDEs in nD: The ADI Method	— (6/22)
	The Alternating Direction Implicit Method ADI Algorithms Implementing ADI Methods	Introduction Crank-Nicolson / ADI on a 2D Square	
4	The ADI Method on a Square		2 of 4

The ADI method will give us a way to solve the combined equation

$$u_t = A_1 u + A_2 u,$$

using the available 1D-solvers as building blocks.

Crank-Nicolson applied to the combined equation gives us

$$\frac{u^{n+1}-u^n}{k} = \frac{1}{2} \left[A_1 u^{n+1} + A_1 u^n \right] + \frac{1}{2} \left[A_2 u^{n+1} + A_2 u^n \right] + \mathcal{O} \left(k^2 \right).$$

Which, with some rearrangement can be written

 $\left[I-\frac{k}{2}A_1-\frac{k}{2}A_2\right]u^{n+1}=\left[I+\frac{k}{2}A_1+\frac{k}{2}A_2\right]u^n+\mathcal{O}\left(k^3\right).$

SAN DIEGO ST UNIVERSIT

- (8/22)

Crank-Nicolson on a Square

Figure: [LEFT] The matrix which must be inverted in each Crank-Nicolson iteration. If we trade storage of the LU-factorization [CENTER, RIGHT] for speed, then here with 6×6 interior points, we end up needing more than 4 times the storage. For 100×100 interior points, the requirement jumps from 49,600 matrix entries, to just over 2,000,000 (a factor of 40). The band-width grows linearly in n, and the LU-factorization fills in the whole bandwidth. In 3D the story gets even worse — with $n \times n \times n$ interior points, the bandwidth is n^2 ...



Êı end up having to invert a penta-diagonal matrix in each iteration.

Systems of PDEs in nD: The ADI Method Peter Blomgren, (blomgren.peter@gmail.com) - (5/22 The Alternating Direction Implicit Method Introduction ADI Algorithms Crank-Nicolson / ADI on a 2D Square Implementing ADI Methods 1 of

The ADI Method on a Square

The ADI method reduces an *n*-dimensional problem to a sequence of *n* one-dimensional problems. We here present the idea in 2D... Let A_1 and A_2 be two linear operators, *e.g.*

$$A_1 u = b_1 \frac{\partial^2}{\partial x^2} u, \quad A_2 u = b_2 \frac{\partial^2}{\partial \gamma^2} u.$$

For the argument to make sense, we must require that we have efficient (convenient) ways of solving the equations

$$w_t = A_i w, \ i = 1, 2,$$

with A_1 , and A_2 as above and a Crank-Nicolson step, these solutions are given by inversion of tri-diagonal matrices.

Êı SAN DIEGO ST

- (7/22)

Introduction Crank-Nicolson / ADI on a 2D Square The Alternating Direction Implicit Method ADI Algorithms Implementing ADI Methods

Introduction Crank-Nicolson / ADI on a 2D Square

The ADI Method on a Square

4 of 4

- (10/22)

2 of 2

Now, we notice that

The ADI Method on a Square

$$(1 \pm A_1)(1 \pm A_2) = 1 \pm A_1 \pm A_2 + A_1A_2.$$

By adding and subtracting $k^2 A_1 A_2 u^{[*]}$ on both sides of the Crank-Nicolson expression we get

$$\begin{bmatrix} I - \frac{k}{2}A_1 - \frac{k}{2}A_2 + \frac{k^2}{4}A_1A_2 \end{bmatrix} u^{n+1}$$

$$= \begin{bmatrix} I + \frac{k}{2}A_1 + \frac{k}{2}A_2 + \frac{k^2}{4}A_1A_2 \end{bmatrix} u^n$$

$$+ \frac{k^2}{4}A_1A_2 \begin{bmatrix} u^{n+1} - u^n \end{bmatrix} + \mathcal{O}\left(k^3\right).$$
Peter Blomgren, (blomgren.peter@gmail.com) Systems of PDEs in *n*D: The ADI Method - (9/22)
The Alternating Direction Implicit Method
ADI Algorithms
Implementing ADI Methods D'Yakonov
Boundary Conditions for ADI Schemes 1 of 2

ADI Algorithms: Peaceman-Rachford

There are several approaches to solving the ADI scheme, one commonly used approach is the Peaceman-Rachford algorithm, which also explain the origin of the name alternating direction implicit method:

$$\begin{bmatrix} I - \frac{k}{2}A_{1,h} \end{bmatrix} v^{n+1/2} = \begin{bmatrix} I + \frac{k}{2}A_{2,h} \end{bmatrix} v^{n},$$
$$\begin{bmatrix} I - \frac{k}{2}A_{2,h} \end{bmatrix} v^{n+1} = \begin{bmatrix} I + \frac{k}{2}A_{1,h} \end{bmatrix} v^{n+1/2}.$$

In the first half-step, the x-direction is implicit, and the y-direction explicit, and in the second half-step the roles are reversed.

Is this scheme equivalent to the ADI scheme we derived?!? — It looks quite different!

Peter Blomgren, {blomgren.peter@gmail.com}

Systems of PDEs in nD: The ADI Method

f

SAN DIEGO STAT

— (11/22)

3 of 4

We can factor this, and use the fact that $u^{n+1} = u^n + O(k)$ to embed the last term on the right-hand-side into the $\mathcal{O}(k^3)$ -term:

$$\left[I-\frac{k}{2}A_{1}\right]\left[I-\frac{k}{2}A_{2}\right]u^{n+1}=\left[I+\frac{k}{2}A_{1}\right]\left[I+\frac{k}{2}A_{2}\right]u^{n}+\mathcal{O}\left(k^{3}\right).$$

Now, if we want to advance the solution numerically, we can discretize this equation, and here when $A_1 = b_1 u_{xx}$, $A_2 = b_2 u_{yy}$, the matrices corresponding to $I - k/2A_i$ will be tridiagonal and can be inverted quickly using the Thomas algorithm.

We get the discretized ADI scheme

$$\left[I-\frac{k}{2}A_{1,h}\right]\left[I-\frac{k}{2}A_{2,h}\right]v^{n+1}=\left[I+\frac{k}{2}A_{1,h}\right]\left[I+\frac{k}{2}A_{2,h}\right]v^{n}.$$

Systems of PDEs in nD: The ADI Method Peter Blomgren, (blomgren.peter@gmail.com)

The Alternating Direction Implicit Method **ADI** Algorithms Implementing ADI Methods

Peaceman-Rachford D'Yakonov Boundary Conditions for ADI Schemes

ADI Algorithms: Peaceman-Rachford

We have.

$$\begin{bmatrix} I - \frac{k}{2} A_{1,h} \end{bmatrix} v^{n+1/2} = \begin{bmatrix} I + \frac{k}{2} A_{2,h} \end{bmatrix} v^{n},$$
$$\begin{bmatrix} I - \frac{k}{2} A_{2,h} \end{bmatrix} v^{n+1} = \begin{bmatrix} I + \frac{k}{2} A_{1,h} \end{bmatrix} v^{n+1/2}.$$

Hence.

$$\begin{bmatrix} I - \frac{k}{2}A_{1,h} \end{bmatrix} \begin{bmatrix} I - \frac{k}{2}A_{2,h} \end{bmatrix} v^{n+1} = \begin{bmatrix} I - \frac{k}{2}A_{1,h} \end{bmatrix} \begin{bmatrix} I + \frac{k}{2}A_{1,h} \end{bmatrix} v^{n+1/2}$$
$$= \begin{bmatrix} I + \frac{k}{2}A_{1,h} \end{bmatrix} \begin{bmatrix} I - \frac{k}{2}A_{1,h} \end{bmatrix} v^{n+1/2} = \begin{bmatrix} I + \frac{k}{2}A_{1,h} \end{bmatrix} \begin{bmatrix} I + \frac{k}{2}A_{2,h} \end{bmatrix} v^{n}.$$

Note that we do not need $A_{1,h}A_{2,h} = A_{2,h}A_{1,h}$ for this to hold. Systems of PDEs in nD: The ADI Method Peter Blomgren, (blomgren.peter@gmail.com)

SAN DIEGO ST

- (12/22)

Peaceman-Rachford D'Yakonov **Boundary Conditions for ADI Schemes**

ADI Algorithms: D'Yakonov

The D'Yakonov scheme is a direct splitting of the ADI scheme we originally derived:

$$\begin{bmatrix} I - \frac{k}{2} A_{1,h} \end{bmatrix} v^{n+1/2} = \begin{bmatrix} I + \frac{k}{2} A_{1,h} \end{bmatrix} \begin{bmatrix} I + \frac{k}{2} A_{2,h} \end{bmatrix} v^n$$
$$\begin{bmatrix} I - \frac{k}{2} A_{2,h} \end{bmatrix} v^{n+1} = v^{n+1/2},$$

Other ADI-type schemes can be derived starting with other basic schemes (we worked from Crank-Nicolson), e.g. the Douglas-Rachford method (Strikwerda pp. 175–176) is derived based on backward-time central-space.

Peter Blomgren, $\langle \texttt{blomgren.peter@gmail.com} \rangle$	Systems of PDEs in nD: The ADI Method	— (13/22)
The Alternating Direction Implicit Method ADI Algorithms Implementing ADI Methods	Peaceman-Rachford The Mitchell-Fairweather Scheme Mixed (u_{xy}) Derivative Terms	
Implementing ADI Methods		1 of (

We consider Peaceman-Rachford on a grid, where

 $(x_{\ell}, y_m) = (\ell \Delta x, m \Delta y), \ \ell = 0, ..., L, \ m = 0, ..., M.$ We let $\mu_x = k/\Delta x^2$, $\mu_y = k/\Delta y^2$. Further, we let $v_{\ell,m}$ denote the full-step quantity, and $w_{\ell m}$ denote the half-step quantity; if we are not interested in saving the results for all t = kn, we can overwrite these quantities...

We get, the first half-stage

$$-\left[\frac{b_1\mu_x}{2}\right]w_{\ell-1,m} + \left[1+b_1\mu_x\right]w_{\ell,m} - \left[\frac{b_1\mu_x}{2}\right]w_{\ell+1,m}$$
$$= \left[\frac{b_2\mu_y}{2}\right]v_{\ell,m-1} + \left[1-b_2\mu_y\right]v_{\ell,m} + \left[\frac{b_2\mu_y}{2}\right]v_{\ell,m+1},$$

for $\ell = 1, ..., L - 1$, and m = 1, ..., M - 1.

Peaceman-Rachford D'Yakonov **Boundary Conditions for ADI Schemes**

Boundary Conditions for ADI Schemes

Here, we consider Dirichlet boundary conditions $u = \beta(t, x, y)$ specified at the boundary, in the context of the Peaceman-Rachford scheme

$$\begin{bmatrix} I - \frac{k}{2} A_{1,h} \end{bmatrix} v^{n+1/2} = \begin{bmatrix} I + \frac{k}{2} A_{2,h} \end{bmatrix} v^{n},$$
$$\begin{bmatrix} I - \frac{k}{2} A_{2,h} \end{bmatrix} v^{n+1} = \begin{bmatrix} I + \frac{k}{2} A_{1,h} \end{bmatrix} v^{n+1/2}.$$

The correct boundary conditions for the half-step quantity is given by

 $v^{n+1/2} = \frac{1}{2} \left[I + \frac{k}{2} A_{2,h} \right] \beta^n + \frac{1}{2} \left[I - \frac{k}{2} A_{2,h} \right] \beta^{n+1}.$

Where did that come from?!? — Flip the second equation in the scheme, add the two, and solve for $v^{n+1/2}$... And it makes sense, "half" the condition comes from the past, and "half" from the future. SAN DIEGO S UNIVERSIT

Peter Blomgren, $\langle \texttt{blomgren.peter@gmail.com} \rangle$	Systems of PDEs in nD: The ADI Method	— (13/22)	Peter Blomgren, {blomgren.peter@gmail.com}	Systems of PDEs in nD: The ADI Method	— (14/22)
The Alternating Direction Implicit Method ADI Algorithms Implementing ADI Methods	Peaceman-Rachford The Mitchell-Fairweather Scheme Mixed (u_{xy}) Derivative Terms		The Alternating Direction Implicit Method ADI Algorithms Implementing ADI Methods	Peaceman-Rachford The Mitchell-Fairweather Scheme Mixed (u_{xy}) Derivative Terms	
ementing ADI Methods		1 of 6	Implementing ADI Methods		2 of 6

Ê

Êı SAN DIEGO STAT

SAN DIEGO ST UNIVERSIT

Figure: "Active" points in the first half-step, the interior points are active both for the old v-layer and the w-layer which is being computed. Also, the boundary values at the top $v_{\ell M}$ and bottom $v_{\ell,0}$ boundaries are active, and so are $w_{0,m}$ (left) and $w_{\ell,m}$ (right).



SAN DIEGO S

The Alternating Direction Implicit Method ADI Algorithms Implementing ADI Methods	Peaceman-Rachford The Mitchell-Fairweather Scheme Mixed (u_{xy}) Derivative Terms		The Alternating Direction Implicit Method ADI Algorithms Peaceman-Rachford Implementing ADI Methods The Mitchell-Fairweather Scheme Mixed (u _{xy}) Derivative Terms	
Implementing ADI Methods		3 of 6	Implementing ADI Methods	4 of 6
If we enumerate our grid-points in (LEXIOGRAPHICAL) way	n the following		We also need the missing boundary conditions for w $w_{0,m} = \left[\frac{b_{2}\mu_{y}}{4}\right]\beta_{0,m-1}^{n} + \left[\frac{1-b_{2}\mu_{y}}{2}\right]\beta_{0,m}^{n} + \left[\frac{b_{2}\mu_{y}}{4}\right]\beta_{0,m+1}^{n} \\ - \left[\frac{b_{2}\mu_{y}}{4}\right]\beta_{0,m-1}^{n+1} + \left[\frac{1+b_{2}\mu_{y}}{2}\right]\beta_{0,m}^{n+1} - \left[\frac{b_{2}\mu_{y}}{4}\right]\beta_{0,m+1}^{n+1}.$ $w_{L,m} = \left[\frac{b_{2}\mu_{y}}{4}\right]\beta_{L,m-1}^{n} + \left[\frac{1-b_{2}\mu_{y}}{2}\right]\beta_{L,m}^{n} + \left[\frac{b_{2}\mu_{y}}{4}\right]\beta_{L,m+1}^{n} \\ - \left[\frac{b_{2}\mu_{y}}{4}\right]\beta_{L,m-1}^{n+1} + \left[\frac{1+b_{2}\mu_{y}}{2}\right]\beta_{L,m}^{n+1} - \left[\frac{b_{2}\mu_{y}}{4}\right]\beta_{L,m+1}^{n+1}.$	
then we get $(M - 1)$ tridiagonal systems (one for each "row"), with $(L - 1)$ unknowns.		For $m = 1, \ldots, M - 1$ ($m = 0$, and $m = M$ are not needed).	San Diego State University	
Peter Blomgren, <code>{blomgren.peter@gmail.com}</code>	Systems of PDEs in nD: The ADI Method	— (17/22)	Peter Blomgren, (blomgren.peter@gmail.com) Systems of PDEs in nD: The ADI Method -	— (18/22)
The Alternating Direction Implicit Method ADI Algorithms Implementing ADI Methods	Peaceman-Rachford The Mitchell-Fairweather Scheme Mixed (u_{xy}) Derivative Terms		The Alternating Direction Implicit Method Peaceman-Rachford ADI Algorithms The Mitchell-Fairweather Scheme Implementing ADI Methods Mixed (u _{XY}) Derivative Terms	
Implementing ADI Methods		5 of 6	Implementing ADI Methods	6 of 6

SAN DIEGO STATE UNIVERSITY

— (19/22)

The second half-stage is given by

$$-\left[\frac{b_2\mu_y}{2}\right]v_{\ell,m-1} + \left[1 + b_2\mu_y\right]v_{\ell,m} - \left[\frac{b_2\mu_y}{2}\right]v_{\ell,m+1}$$
$$= \left[\frac{b_1\mu_x}{2}\right]w_{\ell-1,m} + \left[1 - b_1\mu_x\right]w_{\ell,m} + \left[\frac{b_1\mu_x}{2}\right] - w_{\ell+1,m},$$

for $\ell = 1, ..., L - 1$, and m = 1, ..., M - 1.

With the correct grid-ordering, we get (L-1) tridiagonal systems of size (M-1).

Boundary conditions for v are given at time-level (n + 1).

Figure: "Active" points in the second half-step [left], and the appropriate enumeration order of the grid-points [right].



Peaceman-Rachford The Mitchell-Fairweather Scheme Mixed (u_{xy}) Derivative Terms

The Mitchell-Fairweather Scheme

In Strikwerda (pp. 180–181), there is a discussion of the Mitchell-Fairweather scheme, which is an ADI scheme which is second order in time, and fourth order accurate in space:

$$\begin{bmatrix} 1 - \frac{1}{2} \left(b_1 \mu_x - \frac{1}{6} \right) h^2 \delta_x^2 \end{bmatrix} \mathbf{v}^{n+1/2} = \begin{bmatrix} 1 + \frac{1}{2} \left(b_2 \mu_y + \frac{1}{6} \right) h^2 \delta_y^2 \end{bmatrix} \mathbf{v}^n,$$
$$\begin{bmatrix} 1 - \frac{1}{2} \left(b_2 \mu_y - \frac{1}{6} \right) h^2 \delta_y^2 \end{bmatrix} \mathbf{v}^{n+1} = \begin{bmatrix} 1 + \frac{1}{2} \left(b_1 \mu_x + \frac{1}{6} \right) h^2 \delta_x^2 \end{bmatrix} \mathbf{v}^{n+1/2},$$

with Dirichlet boundary conditions for $v^{n+1/2}$

$$\begin{split} \mathbf{v}^{n+1/2} &= \frac{1}{2b_1\mu_x} \left\{ \left(b_1\mu_x + \frac{1}{6} \right) \left[1 + \frac{1}{2} \left(b_2\mu_y + \frac{1}{6} \right) h^2 \delta_y^2 \right] \beta^n \right. \\ &+ \left(b_1\mu_x - \frac{1}{6} \right) \left[1 - \frac{1}{2} \left(b_2\mu_y - \frac{1}{6} \right) h^2 \delta_y^2 \right] \beta^{n+1} \right\}. \quad \underbrace{\mathbf{Peter Blomgren}}_{\text{Derivative}} \end{split}$$
Peter Blomgren, (blomgren.peter@gmail.com) Systems of PDEs in *n*D: The ADI Method - (21/22)

Peaceman-Rachford The Mitchell-Fairweather Scheme Mixed (u_{xy}) Derivative Terms

ADI with Mixed (u_{xy}) Derivative Terms

It has been shown that no ADI scheme involving only the time levels n+1 and n can be second-order accurate when $b_{12} \neq 0$ (*i.e.* when we have mixed derivatives).

A second-order accurate modification of the Peaceman-Rachford scheme is given by

$$\begin{bmatrix} 1 - \frac{k}{2}b_{11}\delta_x^2 \end{bmatrix} v^{n+1/2} = \begin{bmatrix} 1 + \frac{k}{2}b_{22}\delta_y^2 \end{bmatrix} v^n + kb_{12}\delta_{0x}\delta_{0y} \begin{bmatrix} \frac{3}{2}v^n - \frac{1}{2}v^{n-1} \end{bmatrix},$$
$$\begin{bmatrix} 1 - \frac{k}{2}b_{22}\delta_y^2 \end{bmatrix} v^{n+1} = \begin{bmatrix} 1 + \frac{k}{2}b_{11}\delta_x^2 \end{bmatrix} v^{n+1/2} + kb_{12}\delta_{0x}\delta_{0y} \begin{bmatrix} \frac{3}{2}v^n - \frac{1}{2}v^{n-1} \end{bmatrix},$$

with Dirichlet boundary conditions for $v^{n+1/2}$

$$v^{n+1/2} = \frac{1}{2} \left(1 + \frac{k}{2} b_{22} \delta_y^2 \right) \beta^n + \frac{1}{2} \left(1 - \frac{k}{2} b_{22} \delta_y^2 \right) \beta^{n+1}.$$
Peter Blomgren, (blomgren.peter@gmail.com) Systems of PDEs in *n*D: The ADI Method - (22/22)